



**RLKU12-50JFNA**

1/2" RADIAFLEX® RLKU Cable, A-series



- RADIAFLEX® functions as a distributed antenna to provide communications in tunnels, mines and large building complexes and is the solution for any application in confined areas.
- Slots in the copper outer conductor allow a controlled portion of the internal RF energy to be radiated into the surrounding environment. Conversely, a signal transmitted near the cable will couple into the slots and be carried along the cable length.
- RADIAFLEX® is used for both one-way and two-way communication systems and because of its broadband capability, a single radiating cable can handle multiple communication systems simultaneously.
- This RADIAFLEX® radiating cable utilize a low-loss cellular polyethylene foam dielectric and a smooth copper outer conductor which offers a superior electrical performance together with good bending properties.

**Features / Benefits**

- Ultra wideband from 30 MHz to 2700 MHz
- For applications in tunnels and buildings
- Low coupling loss variations

**Technical Features**

**STRUCTURE**

Cable Type	RLKU
Size	1/2
Inner Conductor Material	Copper Clad Aluminum Wire
Outer Conductor Material	Overlapping Copper Strip
Jacket	JFN
Jacket Description	Halogen free, non corrosive, flame and fire retardant, low smoke, polyolefin
Slot Design	Groups of vertical slots at short intervals
Indication of Slot Alignment	Bulge atop slots

**MECHANICAL SPECIFICATION**

Diameter Inner Conductor	4.4mm (0.17in)
Diameter Outer Conductor	11.4mm (0.45in)
Minimum Bending Radius	200mm (7.9in)
Cable Weight	0.23kg/m (0.16lb/ft)
Tensile Force	1,300N (292lb)
Recommended / Maximum Clamp Spacing	0.5m (1.6ft)
Minimum Distance to Wall	80mm (3.15in)



**RLKU12-50JFNA**

1/2" RADIAFLEX® RLKU Cable, A-series

**ELECTRICAL SPECIFICATION**

Impedance	50 +/- 2 Ω						
Max. Operating Frequency	2,700 MHz						
Velocity	88 %						
Capacitance	76pF/m (23.2pF/ft)						
Inductance	0.19μH/m (0.058μH/ft)						
DC-resistance inner conductor	1.97Ω/km (0.6Ω/kft)						
DC-resistance outer conductor	4.84Ω/km (1.48Ω/kft)						
Stop bands	650-750, 1330-1430, 2025-2100						
Frequency Selection	600	900	1800/1900	2200	2400	2500	2700

**TESTING AND ENVIRONMENTAL**

Operation Temperature	-40 - 85 °C (-40 - 185°F)
Installation Temperature	-25 - 60 °C (-13 - 140°F)
Storage Temperature	-70 - 85 °C (-94 - 185°F)
Compliance	Test methods for fire behaviour of cable : IEC 60754-1/-2 smoke emission: halogen free, non corrosive IEC 61034 low smoke IEC 60332-1 flame retardant IEC 60332-3-24 fire retardant UL1666, ASTM E 662, NES711 and NES713

**ATTENUATION AND COUPLING LOSS**

Frequency, MHz	Longitudinal Loss, dB/100 m (dB/100 ft)	Coupling Loss 50%, dB	Coupling Loss 95%, dB
75	2.17 (0.66)	49 (53)	59 (63)
150	3.10 (0.94)	57 (61)	68 (72)
450	5.74 (1.75)	65 (68)	76 (79)
800	8.75 (2.67)	57 (59)	63 (65)
870	9.21 (2.81)	58 (60)	64 (66)
900	9.40 (2.86)	58 (60)	63 (66)
960	9.73 (2.97)	58 (60)	64 (66)
1800	21.97 (6.70)	55 (57)	65 (67)
1900	22.71 (6.92)	55 (57)	65 (67)
2000	23.48 (7.16)	53 (56)	65 (66)
2200	25.47 (7.76)	52 (55)	60 (63)
2400	27.93 (8.51)	52 (54)	60 (63)
2600	30.50 (9.30)	52 (54)	60 (63)

@ 20°C (68°F)

**NOTES**

- Coupling loss as well as longitudinal attenuation of RADIAFLEX® cables are measured by the free space method according to IEC 61196-4.
- Coupling loss values are measured with a radial (below 650 MHz) or parallel (above 650 MHz) orientated dipole antenna.
- The coupling loss values given in brackets are average values of all three spatial orientations (radial, parallel and orthogonal) of dipole antenna.
- Coupling loss values are given with a tolerance of +5 dB and longitudinal loss values with a tolerance of +5%. Note: Measured values below nominal are better. They are not limited by any tolerance-range.



**RLKU12-50JFNA**

1/2" RADIAFLEX® RLKU Cable, A-series

- In case of a conflict of operational and stop band, please contact RFS for further assistance.
- As with any radiating cable, the performance in building or tunnel environments may deviate from figures based on free space method.

;